

1 Requirements


The Talk-A-Phone integration works with any exacqVision system. This document assumes that the exacqVision server and the Talk-A-Phone are both installed and running.

Minimum software requirements:


- exacqVision version 4.2 or later
- Talk-A-Phone VOIP-500 firmware version 1.0.1.10 or later

2 Configuration


1. Browse to the IP address of the Talk-A-Phone and log in.
2. Click on **Digital Outputs** and then the **Scripts** submenu.
3. Select a script slot and assign a label such as **Activate Camera**.
4. Enter a script in the box, such as **echo "activate camera_1" | nc 192.168.3.117 30000**. This script would send ASCII message "activate camera_1" to the the exacqVision server with IP address 192.168.3.117 on port 30000.
5. Click **Apply**.
6. Click on the **Events** sub menu under **Digital Outputs**.
7. Select the checkbox under **Button Events**, select **INITIATED** from the drop-down list, and select script you created in step 4.
8. Click **Apply**.



9. In exacqVision Client, open the **Serial Profiles** page for the exacqVision server from the site tree.
10. Click the **New** button under **Existing Profiles**.
11. Enter a new **Profile Name**, such as **Talkaphone**.
12. Under **Event Key Words**, enter the key word you used in step 4.
13. Click **Apply**.



14. In exacqVision Client, select **Serial Ports** for the exacqVision server from the site tree.
15. Click the **New** button.
16. In the **Use** column under the **IP** section, select **POS** from the drop-down list.
17. In the **Name** column, enter a name such as **Talkaphone**.
18. In the **Profile** column, select the previously created profile from the drop-down list.
19. In the **Type** column, select **TCP Listener** from the drop-down list.
20. In the **Address** column, enter the IP address of the Talk-A-Phone.
21. In the **Port** column, enter the port number used in step 4.
22. Click **Apply**.



23. Configure event linking and monitoring as discussed in the exacqVision manual (press F1 to view) for features such as recording video or triggering a PTZ preset movement when the Talk-A-Phone call button is activated.